Fingertip Pulse Oximeter



The **Roscoe OTC Fingertip Pulse Oximeter** allows you to monitor and maintain pulse and oxygen saturation levels on-the-go. Accurate and fast oxygen level and heart rate measuring technology is ideal for sports enthusiasts during strenuous activities or mountain climbing. Recommended for spot-check monitoring only. No prescription required.



PRODUCT FEATURES:

- Approved for over-the-counter retail sale
- Large easy-to-read display
- Soft silicone padding for a comfortable fit
- One-button operation
- Up to 30 hours of use with batteries
- Auto-off function
- Low battery indicator
- Manual, lanyard and two AAA alkaline batteries included
- Attractive retail packaging
- One-year limited warranty

PRODUCT SPECIFICATIONS:

| Dimensions: | 2.25"L x 1.25"W x 1.25"H | |
|------------------------|--|--|
| Weight: | 1.6 oz (including batteries) | |
| Display Type: | LED | |
| Display Range: | 0 - 99% | |
| Measurement Range: | 0 - 100% | |
| Accuracy: | 70% - 100% ±3% | |
| Resolution: | ±2% for SpO2 | |
| Operating Temperature: | 41-105°F (5~40°C) | |
| Storage Temperature: | -4 -131°F (-20~55°C) | |
| Ambient Humidity: | 15%-80% in operation; ≤93% in storage | |

| Item # | Description | UPC | UOM |
|---------|---------------------------------|--------------|------|
| POX-ROS | Roscoe Fingertip Pulse Oximeter | 092237621981 | each |